

Blind Multiuser Receiving Scheme Based on Oriented Minimum Output Energy Criterion

Hongrui Jiang*, Kyung-Sup Kwak* *Regular Members*

ABSTRACT

Based on oriented minimum output energy (OMOE) criterion, a new blind multiuser receiving scheme of linear minimum mean square error (MMSE) detector is proposed, then an adaptive algorithm for implementing the new scheme is given by the steepest descent method, and the convergence property of the algorithm is analyzed in this paper. The numerical results demonstrate the performance of the proposed scheme.

I. Introduction

Blind multiuser detector [1][2], which doesn't require the prior knowledge of the signature waveform and timing of all users, has received considerable attention. Honig M. etc. [2] proposed blind multiuser detection earlier, and basing on constrained minimum output energy (MOE) criterion, they obtained a blind adaptive Scheme of linear minimum-mean-square-error (MMSE) detector [3] which is realized by solving a constrained optimization problem, that is, it requires detector to satisfy the form of standard criterion. However, in the iteration algorithm, the projection of the quadrature component often needs to be calculated, which brings up difficulty in solving problem.

In fact, the form of standard criterion is nonessential to a linear detector. The substance is that the detector is required to be the same quadrant with the user address code, that is, the projection on the user address code is positive. Based on the idea, a non-constrained optimization criterion is given in this paper. A new blind multiuser receiving scheme of linear MMSE is obtained by solving the optimization problem.

Notations: Column vectors and matrices are denoted by boldface lower and upper case letters, respectively. The superscript T stands for

transpose, and I_n denotes the $n \times n$ identity matrix.

II. Signal Model

Consider a synchronous baseband DS-SS system with K users. The received signal is given by

$$r(t) = \sum_{k=1}^K A_k b_k s_k(t) + n(t), \quad t \in [0, T] \quad (1)$$

where A_k , b_k and $s_k(t)$ denote, respectively, the received amplitude, transmitted symbol and normalized signaling waveform of the k th user, and $n(t)$ is the additive white Gaussian noise (AWGN) with zero mean and variance σ^2 . For simplicity, it is assumed that b_k is a binary phase-shift keying (BPSK) signal, that is, $b_k \in \{\pm 1\}$ is assumed to be independent equiprobable random variables, and that $s_k(t)$ is real and supported only on the interval $[0, T]$, which is of the form

$$s_k(t) = \sum_{j=0}^{N-1} c_j^k \phi(t - jT_c), \quad t \in [0, T] \quad (2)$$

where N is the processing gain, $(c_0^k, c_1^k, \dots, c_{N-1}^k)$ is a signature sequence of ± 1 's assigned to the k th user, and ϕ is a

* 인하대학교 전자공학과 통신공학연구소
 논문번호:010341-11.6, 접수일자: 2001년 11월 16일

normalized chip waveform of duration T_c where $NT_c = T$. The extension to the MPSK signal and complex signaling is straight-forward.

At the receiver, chip-matched filtering followed by chip rate sampling yields a N -vector of chip-matched filter output samples within a symbol interval T .

$$\mathbf{r} = \sum_{k=1}^K A_k b_k \mathbf{s}_k + \mathbf{n}, \quad (3)$$

where $\mathbf{s}_k = (1/\sqrt{N})[c_0^k, \dots, c_{N-1}^k]^T$ is the normalized signature waveform vector of the k th user, \mathbf{n} is an AWGN vector with mean $\mathbf{0}$ and covariance matrix $\sigma^2 \mathbf{I}_N$. Moreover, assume that the vectors $\{\mathbf{s}_k\}_{k=1}^K$, also called signal vectors, are independent.

III. The New Blind Multiuser Detection Scheme

Linear multiuser detector is composed of a correlator and a decision threshold, that is

$$b = \text{sgn}(\mathbf{w}^T \mathbf{r}), \quad (4)$$

where $\mathbf{w} \in \mathbb{R}^N$. For any $\mu > 0$, linear detector \mathbf{w} and $\mu\mathbf{w}$ are equivalent. It's easy to deduce that their error rates, asymptotic efficiencies and signal-to-interference rates are the same.

The data receiving of user 1 is considered. A linear MMSE detector \mathbf{w}_{MSE} is obtained by minimum mean square error (MSE) [3].

$$MSE(\mathbf{w}) = E\{(\mathbf{w}^T \mathbf{r} - A_1 b_1)^2\} \quad (5)$$

and

$$\mathbf{w}_{MSE} = A_1^2 \mathbf{R}^{-1} \mathbf{s}_1 \quad (6)$$

where

$$\mathbf{R} = E\{\mathbf{r}\mathbf{r}^T\} = \sum_{k=1}^K A_k^2 \mathbf{s}_k \mathbf{s}_k^T + \sigma^2 \mathbf{I}_N \quad (7)$$

is autocorrelation matrix of receiving signal. When directly solving detector \mathbf{w}_{MSE} , we require to know

the training sequence, so there is no method to realize the blind multiuser receiving.

According to constrained MOE criterion [2],

$$MOE(\mathbf{w}) = E\{(\mathbf{w}^T \mathbf{r})^2\}, \text{ s.t. } \mathbf{w}^T \mathbf{s}_1 = 1. \quad (8)$$

A blind multiuser receiving scheme of linear MMSE detector is given. The optimization detector satisfying above criterion is

$$\mathbf{w}_{MOE} = \frac{1}{\mathbf{s}_1^T \mathbf{R}^{-1} \mathbf{s}_1} \mathbf{R}^{-1} \mathbf{s}_1 \quad (9)$$

MOE criterion is a constrained optimization problem which requires detector to satisfy standard criterion form, that is, $\mathbf{w}^T \mathbf{s}_1 = 1$. But in fact, the criterion form is nonessential, and its substance is to require that \mathbf{w} and \mathbf{s}_1 locate in the same quadrant in space, that is, $\mathbf{w}^T \mathbf{s}_1 > 0$. According to the idea, we consider the following optimization criterion.

$$J(\mathbf{w}) = E\{(\mathbf{w}^T \mathbf{r})^2\} + (\mathbf{w}^T \mathbf{s}_1 - m)^2, \quad (10)$$

where $m > 0$ is any constant. And it may be proved that $J(\mathbf{w})$ has unique extreme point

$$\mathbf{w}_{\min} = \frac{m}{1 + \mathbf{s}_1^T \mathbf{R}^{-1} \mathbf{s}_1} \mathbf{R}^{-1} \mathbf{s}_1. \quad (11)$$

Comparing the expressions (6) and (11), we know that linear detector \mathbf{w}_{\min} is equivalent to MMSE detector \mathbf{w}_{MSE} . Therefore, according to optimization (10), we can obtain a blind multiuser receiving scheme of linear MMSE detector.

The derivation process of expression (11) is given in the following. According to grads of $J(\mathbf{w})$, we get

$$\begin{aligned} \nabla J(\mathbf{w}) &= 2E\{\mathbf{r}\mathbf{r}^T\}\mathbf{w} + 2(\mathbf{w}^T \mathbf{s}_1 - m)\mathbf{s}_1 \\ &= 2(\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T)\mathbf{w} - 2m\mathbf{s}_1 \end{aligned} \quad (12)$$

Therefore we know

$$\begin{aligned} \mathbf{w}_{\min} &= m(\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T)^{-1} \mathbf{s}_1 \\ &= m(\mathbf{I}_N + \mathbf{R}^{-1} \mathbf{s}_1 \mathbf{s}_1^T)^{-1} \mathbf{R}^{-1} \mathbf{s}_1 \end{aligned}$$

$$\begin{aligned}
 &= m[\mathbf{I}_N - \mathbf{R}^{-1}\mathbf{s}_1(1 + \mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1)^{-1}\mathbf{s}_1^T] \mathbf{R}^{-1}\mathbf{s}_1 \\
 &= m[\mathbf{R}^{-1}\mathbf{s}_1 - \mathbf{R}^{-1}\mathbf{s}_1(1 + \mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1)^{-1}\mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1] \\
 &= \frac{m}{1 + \mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1} \mathbf{R}^{-1}\mathbf{s}_1
 \end{aligned} \tag{13}$$

The above third equation is obtained by inverse operation formula of the following matrix.

$$(\mathbf{I} + \mathbf{a}\mathbf{b}^T)^{-1} = \mathbf{I} - \mathbf{a}(\mathbf{I} + \mathbf{b}^T \mathbf{a})^{-1} \mathbf{b}^T \tag{14}$$

Remark 1: Optimization criterion (10) without constrained condition doesn't require to detector to satisfy standard criterion form. Its second term insures that directions of \mathbf{w} and \mathbf{s}_1 are identical, which plays the role of orientation, that is, its projection $\mathbf{w}^T \mathbf{s}_1 > 0$. Therefore, optimization criterion (10) may be named as oriented minimum output energy (OMOE) criterion.

Remark 2: Linear detector multiplies a positive scaling factor, and its performance doesn't change. Therefore, according to optimization (10), we know the selection of the parameter m doesn't affect the performance of the detector.

Remark 3:

When $m = 1 + 1/(\mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1)$, $\mathbf{w}_{\min}^T \mathbf{s}_1 = 1$ where $\mathbf{w}_{\min} = \mathbf{w}_{MOE}$.

Remark 4:

When $m = A_1^2 (1 - \mathbf{s}_1^T \mathbf{R}^{-1}\mathbf{s}_1)$, $\mathbf{w}_{\min} = \mathbf{w}_{MSE}$.

IV. Blind Adaptive Algorithm

Using steepest-descent algorithm [3], we can get a blind adaptive algorithm of linear MMSE detector basing on optimization criterion (10).

$$\mathbf{w}(n+1) = \mathbf{w}(n) - \frac{1}{2} \mu \nabla J(\mathbf{w}(n)) \tag{15}$$

where $\nabla J(\mathbf{w})$ is obtained from (12). It can be proved that above algorithm converges if and only if

$$0 < \mu < \frac{2}{\lambda_{\max}}, \tag{16}$$

where λ_{\max} is the maximum eigenvalue of matrix

$$\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T.$$

The convergence of the algorithm is proved in the following. Define vector error

$$\mathbf{e}(n) = \mathbf{w}(n) - \mathbf{w}_{\min}. \tag{17}$$

Because of $\nabla J(\mathbf{w}_{\min}) = 0$, equation (14) is equivalent to

$$\mathbf{e}(n+1) = \mathbf{e}(n) - \mu[\nabla J(\mathbf{w}(n)) - \nabla J(\mathbf{w}_{\min})]. \tag{18}$$

According to (12), we further get

$$\mathbf{e}(n+1) = [\mathbf{I}_N - \mu(\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T)] \mathbf{e}(n). \tag{19}$$

Because matrix $\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T$ is positive definite, there exists orthogonal matrix \mathbf{Q} which makes $\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T = \mathbf{Q}^T \mathbf{\Lambda} \mathbf{Q}$ where $\mathbf{\Lambda} = \text{diag}(\lambda_1, \lambda_2, \dots, \lambda_N)$ is diagonal matrix, and λ_i is the eigenvalue of matrix $\mathbf{R} + \mathbf{s}_1 \mathbf{s}_1^T$. If we define $\mathbf{u}(n) = \mathbf{Q}\mathbf{e}(n)$, then equation (18) may be changed as

$$\mathbf{u}(n+1) = (\mathbf{I}_N - \mu \mathbf{\Lambda}) \mathbf{u}(n) \tag{20}$$

or

$$u_i(n+1) = (1 - \mu \lambda_i) u_i(n), \quad i = 1, \dots, N. \tag{21}$$

Therefore, iteration process (19) converges if and only if

$$0 < \mu < \frac{2}{\lambda_i}, \quad i = 1, \dots, N, \tag{21}$$

that is, condition (15) comes into existence. Because the convergence of algorithm (14) and iteration process (18), (19) are equivalent, algorithm (14) converges if and only if condition (15) comes into existence.

In the real application, the autocorrelation \mathbf{R} of receiving signal can use its estimate value

$$\hat{\mathbf{R}}(n) \triangleq \frac{1}{n} \sum_{i=1}^n \mathbf{r}(i) \mathbf{r}(i)^T \tag{23}$$

to calculate. The blind adaptive algorithm of linear MMSE detector based on optimization criterion (10) is summarized as the following:

Algorithm:

$$\hat{\mathbf{R}}(n) = \frac{n-1}{n} \hat{\mathbf{R}}(n-1) + \frac{1}{n} \mathbf{r}(n) \mathbf{r}(n)^T \quad (24)$$

$$\frac{1}{2} \nabla J(\mathbf{w}(n)) = [\hat{\mathbf{R}}(n) + \mathbf{s}_1 \mathbf{s}_1^T] \mathbf{w}(n) - m \mathbf{s}_1 \quad (25)$$

$$\mathbf{w}(n+1) = \mathbf{w}(n) - \frac{1}{2} \mu \nabla J(\mathbf{w}(n)) \quad (26)$$

$$\hat{\mathbf{R}}(0) = \mathbf{I}_N \quad (27)$$

$$\mathbf{w}(0) = \mathbf{w}_0 \quad (28)$$

V. Simulation Analysis

In the following, the performance of blind adaptive detector given in this paper is analysed through computer simulation. The performance measure is the output signal-to-interference ratio (*SIR*):

$$\begin{aligned} SIR(n) &= \frac{E\{\mathbf{w}(n)^T \mathbf{r}\}}{Var\{\mathbf{w}(n)^T \mathbf{r}\}} \\ &= \frac{A_1^2 [\mathbf{w}(n)^T \mathbf{s}_1]^2}{\sum_{k=2}^K A_k^2 [\mathbf{w}(n)^T \mathbf{s}_k]^2 + \sigma^2 \mathbf{w}(n)^T \mathbf{w}(n)}. \end{aligned} \quad (29)$$

We consider a synchronous DS/CDMA system with processing gain $N=10$ and number of user $K=5$. The spreading sequences $\{c_j^k, j=0, 1, \dots, N-1\}$ are randomly generated. The desired user is user 1, and other users are multiple-access interference (MAI). The MAI intensity is $MAI_k = 10 \log_{10}(A_k^2/A_1^2) = 20$ dB ($k=2 \sim 6$). The channel interference is white Gaussian noise, and the signal-to-noise ratio is $SNR_1 = 10 \log_{10}(A_1^2/\sigma^2) = 20$ dB. Simulation results are shown in Fig.1 where all data is the averaged value of 30 simulation results. Curves represent SIRs of OMOE and MOE, and straight dashed represents optimization value of MMSE detector.

In order to compare conveniently, we use the steepest descent methods for all iteration algorithms and choose the same steps. From Fig.1, the performance of OMOE and MOE corresponds and is close to optimization value of

MMSE detector.




Fig. 1 Output SIR of detector

VI. Conclusion

In this paper, basing on an OMOE criterion, we have presented a new blind receiving scheme of linear MMSE detector. OMOE without constrained condition doesn't require detector to satisfy standard criterion form, which makes it convenient to find solution. The steepest descent method is used, corresponding blind adaptive detection algorithm is given, and the convergence condition of the algorithm is analysed. It is shown by simulation results that the performance of OMOE and MOE are equivalent, and OMOE possesses strong capability to constrain interference.

References

- [1] Madhow U. "Blind adaptive interference suppression for direct-sequence CDMA," *Proceedings of the IEEE*, 86(10), pp. 2049-2069, 1998.
- [2] Honig M, Madhow U and Verdu S., "Blind adaptive multiuser detection," *IEEE Trans. Information Theory*, 41(4), pp. 944-960, 1995.
- [3] Madhow U, Honig M., "MMSE interference suppression for direct-sequence spread-spectrum CDMA," *IEEE Trans. communications*, 42(12), pp. 3178-3188, 1994.
- [4] Haykin S., *Adaptive filter theory, third edition*,

Prentice Hall, 1996.

장 홍 예(Hongrui Jiang)



1993~1997: B.S., Dept. of Microwave Telecommunication Engineering, Xidian University, Xian City, China

1997~2000: M.S., majoring in Processing of Signal & Information, Dept. of Electronic Information, Guilin Institute of

Electronic Technology, Guilin City, China

2001~present: Ph.D. student, majoring in Electronic Telecommunication Engineering, Dept. of Electronic Engineering, Inha University, Korea
<Main Interesting fields> Neural Networks, Telecommunication and so on

곽 경 섭(Kyung-Sup Kwak)



1977년 2월: 인하대학교 전기공학과 졸업(공학사)

1981년 12월: 미국 University of Southern California 공학석사

1988년 2월: 미국 University of Southern California 공학 박사(통신이론 및 시스템)

1988년 2월~1989년 2월: 미국 Hughes Network Systems 연구원

1989년 2월~1990년 3월: 미국 IBM Network Analysis Center 연구원

1996년 3월~현재: 인하대학교 정보통신공학부 교수

1999년 1월~현재: 통신학회 상임이사

2000년 3월~현재: 정보통신전문대학원 원장

<주관심 분야> 위성 및 이동 통신, 멀티미디어 통신